

## DESCRIPTION

FIELD INTERPOLATION METHOD DETERMINATION DEVICE

5

## TECHNICAL FIELD

The present invention relates to a field interpolation method determination device for determining whether to perform either an inter-field interpolation method or an intra-field interpolation method to combine fields of an inputted interlaced signal into frames and thereby to provide conversion to a progressive signal.

## BACKGROUND ART

Interlaced signals to be converted into progressive signals are classified into ordinary signals for images scanned by interlaced scanning and interlaced signals converted from progressive signals. A typical example of the latter is a telecine-converted signal.

In a 2-2 pulldown method, which is a telecine conversion method, the telecine-converted signal is generated as follows. Firstly, frames of a 24 frame-per-second movie film are sequentially scanned to generate a 24 frame-per-second progressive signal. Then, each frame (parent frame) of the progressive signal is converted into an odd field of an interlaced signal and an even field following immediately thereafter.

For example, the first frame of a movie film (a first parent frame of the progressive signal) is converted into first and second fields, while the second frame of the movie film (a second parent frame of the progressive signal) is converted into third and fourth  
5 fields.

Thus, visual images in the first and second fields converted from the same parent frame are similar to each other, and therefore there is only a small difference between the visual images. As for the second and third fields converted from different parent  
10 frames, an inter-field visual difference reflects a difference between the parent frames, and therefore is large as compared to the former case. That is, a difference between adjacent fields varies alternately between large and small among the fields in accordance with a parent frame-to-field relationship.

15 Such a characteristic of the telecine-converted signal also holds for a 60 field-per-second interlaced signal obtained by 2-2 pulldown-converting a progressive signal captured by a 30P video camera for generating a 30 frame-per-second progressive video signal.

20 Also, in a 2-3 pulldown method which is used for telecine conversion to an NTSC (60 field-per-second) interlaced signal, one frame of the movie film is converted into two fields, and the next frame is converted into 3 fields, and the conversion pattern is repeated for every two frames. A 2-3 pulldown  
25 telecine-converted signal also has the above characteristic

because it exhibits a regular pattern in which an inter-field pixel level difference varies in accordance with a parent frame-to-field relationship.

Japanese Laid-Open Patent Publication No. 9-18784 (claiming  
5 a priority of US application No. 94-366799) discloses a field interpolation method determination device a field interpolation method determination device which identifies whether an input interlaced signal is a telecine-converted signal based on an inter-field difference of the input interlaced signal, and  
10 determines a field interpolation method.

Referring to FIG. 10, a video signal processing device having incorporated therein a conventional field interpolation method determination device is described. A video signal processing device 200 shown in the figure converts an interlaced signal into  
15 a progressive signal by carrying out inter-field interpolation only when an interlaced signal is a telecine-converted signal, while intra-field interpolation is carried out if it is not the telecine-converted signal.

The video signal processing device 200 includes an input  
20 terminal 1, a field memory 2, a field memory 4, a subtractor 6, a field interpolation method determination section 108, an ODD/EVEN detection section 10, a first switch 12, a line memory 14, a 2-line interpolation section 16, a second switch 18, and a progressive signal generation section 20.

25 The input terminal 1 is supplied with an input interlaced

signal Vin. The field memory 2 outputs a 1-field delay input interlaced signal Vd1 delayed by one field with respect to the input interlaced signal Vin. The 1-field delay input interlaced signal Vd1 is inputted into the progressive signal generation  
5 section 20 where either inter-field interpolation or intra-field interpolation is performed on the signal.

The subtractor 6 obtains a difference in pixel level between the input interlaced signal Vin and the 1-field delay input interlaced signal Vd1, and outputs it as an inter-field pixel level  
10 difference Sp. Note that in the interlaced signal, scanning lines of adjacent fields are displaced by one row from each other. Accordingly, the subtractor 6 obtains a difference between an average pixel level for two adjacent lines in one field and a corresponding pixel level in the other field.

15 The field interpolation method determination section 108 determines whether the input interlaced signal Vin is a telecine-converted signal based on the inter-field pixel level difference Sp. The field interpolation method determination section 108 outputs a field interpolation method instruction signal  
20 Dvp that instructs to perform either the inter-field interpolation or the intra-field interpolation on the 1-field delay input interlaced signal Vd1.

If a field interpolation method instruction signal Dvp, which instructs to perform the inter-field interpolation is inputted,  
25 the second switch 18 selects an inter-field interpolation video

signal Sw1 outputted from the first switch 12, and outputs it as an interpolation video signal Sw2.

The inter-field interpolation signal video Sw1 is either of a 2-field delay input interlaced signal Vd2 and an input  
5 interlaced signal Vin, which respectively correspond to fields before and after the 1-field delay input interlaced signal Vd1, and it is selected as follows.

The ODD/EVEN detection section 10 detects whether the signal corresponds to an odd field or an even field based on the 1-field  
10 delay input interlaced signal Vd1, and outputs a field identification signal Doe which indicates a detection result.

The first switch 12 selects either the 2-field delay input interlaced signal Vd2 or the input interlaced signal Vin based on the field identification signal Doe, and outputs it as the  
15 inter-field interpolation video signal Sw1. Specifically, the first switch 12 outputs the input interlaced signal Vin if the 1-field delay input interlaced signal Vd1 corresponds to an odd field, while it outputs the 2-field delay input interlaced signal Vd2 if the 1-field delay input interlaced signal Vd1 corresponds  
20 to an even field.

The progressive signal generation section 20 interpolates the 1-field delay input interlaced signal Vd1 with the interpolation video signal Sw2 outputted from the second switch  
18 (in this case, either one of the current signal Vin and the  
25 2-field delay input interlaced signal Vd2, which has been selected

by the first switch 12), thereby generating a progressive signal.  
The frame of the thus-generated progressive signal is identical  
to the original parent frame, and enhanced in terms of vertical  
resolution as compared to a frame generated by intra-field  
5 interpolation which will be described later.

On the other hand, if a field interpolation method  
instruction signal Dvp, which instructs to carry out intra-field  
interpolation, is outputted from the field interpolation method  
determination section 108, the second switch 18 selects an  
10 intra-field interpolation video signal Vd1S outputted from the  
2-line interpolation section 16, and outputs it as an interpolation  
video signal Sw2.

The 2-line interpolation section 16 generates an intra-field  
interpolation video signal Vd1S based on a 1-line delay signal  
15 Vd1L, which is obtained by delaying the 1-field delay input  
interlaced signal Vd1 by one line in the line memory 14, and the  
1-field delay input interlaced signal Vd1.

The progressive signal generation section 20 interpolates  
the 1-field delay input interlaced signal Vd1 with the  
20 interpolation video signal Sw2 outputted from the second switch  
18 (in this case, the intra-field interpolation signal Vd1S),  
thereby generating a progressive signal.

The subtractor 6 and the field interpolation method  
determination section 108 shown in FIG. 10 correspond to the  
25 conventional field interpolation method determination device.

Referring to FIG. 11, the conventional field interpolation method determination device is described. FIG. 11 is a block diagram showing a detailed structure of the field interpolation method determination section 108 shown in FIG. 10.

5           The field interpolation method determination section 108 includes an absolute value circuit 81, a pixel difference determination comparator 82, a cumulative adder 83, an inter-field correlation determination comparator 84, a first register 85, a second register 86, a 2-field difference determination comparator  
10 189, an exclusive-OR (EOR) circuit 190, a counter 92, and a count determination comparator 93.

Although not shown, a field pulse VP and a frame pulse FP are generated by a timing generation circuit.

15           The absolute value circuit 81 obtains an absolute value of the inter-field pixel level difference  $Sp$ , which is calculated by the subtractor 6a and corresponds to a difference in level between pixels of the input interlaced signal  $V_{in}$  and the 1-field delay input interlaced signal  $V_{d1}$ , and outputs an inter-field pixel level difference absolute value  $SpA$ .

20           The pixel difference determination comparator 82 compares the inter-field pixel level difference absolute value  $SpA$  with a predetermined first threshold  $X$  to provide a determination as to whether two comparison target fields have at least a great difference (a significant difference) in pixel level to such an  
25 extent that they are considered as being derived from the same

parent frame. As an inter-field pixel difference determination signal  $D_p$ , which indicates a result of the determination, the pixel difference determination comparator 82 outputs "1" if the determination is "significant difference", or outputs "0" if it is "no significant difference".

The cumulative adder 83 outputs an inter-field pixel difference determination cumulative value  $CD_p$  which is obtained by cumulatively summing inter-field pixel difference determination signals  $D_p$ . The inter-field pixel difference determination cumulative value  $CD_p$  is a value which indicates the number of pixels having been determined as having a "significant difference" between fields of the input interlaced signal  $V_{in}$  and the 1-field delay input interlaced signal  $V_{d1}$ . Note that the cumulative adder 83 is reset for each field by the field pulse  $VP$ .

If the inter-field pixel difference determination cumulative value  $CD_p$  is greater than a predetermined threshold  $Y$ , the inter-field correlation determination comparator 84 determines that there is a difference between the fields. Then, it outputs an inter-field correlation determination signal  $D_f$  which indicates a result of the determination.

The value of the inter-field correlation determination signal  $D_f$  is "1" if there is a difference, or outputs "0" if there is no difference.

The first register 85 and the second register 86 are



D-flip-flops, and supplied with the field pulse VP as a clock. An inter-field determination result is supplied to a series circuit composed of the first register 85 and the second register 86. The first register 85 and the second register 86 output an inter-field  
5 difference stored therein to the 2-field difference determination comparator 189 and the EOR circuit 190, respectively.

In the case where outputs of the first register 85 and the second register 86 are respectively "0" and "1", or "1" and "0", differential relationships between two sequential fields in  
10 respective cases are "small and large", and "large and small". That is, they show the above-described characteristic of the telecine-converted interlaced signal. In such a case, the 2-field difference determination comparator 189 determines that the input interlaced signal Vin has been telecine-converted, and outputs  
15 "1" to increment the counter 92.

On the other hand, if the outputs of the first register 85 and the second register 86 are respectively "0" and "0", or "1" and "1", the differential relationships between the two sequential fields are "small and small" or "large and large". That is, they  
20 do not show the above-described characteristic of the telecine-converted interlaced signal. In such a case, the EOR circuit 190 resets the counter 92.

As described above, the counter 92 is incremented or reset. If a count value CDs of the counter 92 reaches a predetermined  
25 value Z, the count determination comparator 93 outputs a field

interpolation method instruction signal Dvp that instructs to perform inter-field interpolation on fields of the input interlaced signal.

In actuality, however, there are various types of visual images, and therefore in some cases, it is not possible to detect a difference between parent frames of even the telecine-converted signal as a difference between fields because there is no difference or only a slight difference between the parent frames. In such a case, the field interpolation method determination device is not able to detect the telecine-converted signal.

For example, in the case of video consisting of continuous still images, where images in two parent frames are identical to each other, a difference between fields converted from different parent frames is naturally small. In such a case, the field interpolation method determination device is not able to detect the difference between the parent frames based on the difference between fields. Consequently, the conventional field interpolation method determination device is not able to detect an inter-field variation pattern specific to the telecine-converted signal, and therefore the interlaced signal is determined not to be the telecine-converted signal.

Also, in visual images of dark scenes, even if they are dynamic images, there is only a small difference in pixel level between parent frames, and therefore a difference between fields converted from different frames is also small. In such a case, similar to

the above case, the field interpolation method determination device determines that the interlaced signal is not the telecine-converted signal.

Also, for example, in the case where interlaced signals for  
5 commercials, etc., which have a different frame correlation, are  
inserted between interlaced signals for a program, correlations  
between parent frames and correlations between fields may vary  
in a specific manner. In such a case, an inter-field difference  
variation pattern specific to the telecine-converted signal varies  
10 in a specific manner, and therefore, similar to the above case,  
the field interpolation method determination device determines  
that the interlaced signals are not telecine-converted signals.

As such, in the case where a difference between at least  
two frames cannot be detected, the conventional field interpolation  
15 method determination device is not able to identify the  
telecine-converted signal, even if the input interlaced signal  
is the telecine-converted signal. As a result, the video signal  
processing device carries out intra-field interpolation until  
input interlaced signals for at least a predetermined number of  
20 fields are continuously determined to be the telecine-converted  
signal. Accordingly, it is often the case where an original parent  
frame cannot be generated with high vertical resolution.

Also, the above conventional technique has been described  
such that in the telecine conversion, a parent frame is generally  
25 converted into an odd field and an even field following immediately

thereafter. In actuality, however, on rare occasion, a telecine-converted signal is obtained by converting the parent frame into an even field and an odd field following immediately thereafter.

5       The conventional field interpolation method determination device selects a frame immediately before or after an interpolation target signal as an interpolation video signal depending on whether the target signal corresponds to an odd frame or an even frame. Accordingly, in a signal where positional relationships between  
10 fields converted from parent frames are reversed, two fields converted from different parent frames are interpolated with each other and converted into one frame. As a result, different images are present in one frame, and therefore video quality of a progressive signal obtained by conversion is considerably  
15 deteriorated.

Therefore, an object of the present invention is to provide a field interpolation method determination device capable of accurately detecting a field-to-frame relationship of an input interlaced signal even if it is not possible, or it is difficult,  
20 to specifically detect a difference between parent frames, thereby determining whether to use either inter-field interpolation or intra-field interpolation to perform an interpolation operation.

#### DISCLOSURE OF THE INVENTION

25       To achieve the above object, the present invention has the

following features.

A first aspect of the present invention is directed to a field interpolation method determination device for determining whether to perform either an inter-field interpolation method or  
5 an intra-field interpolation method to combine fields of an inputted interlaced signal into frames and thereby to provide conversion to a progressive signal, the device comprising:

pixel level difference detection means for detecting a pixel level difference between an input interlaced signal and a 1-field  
10 delay input interlaced signal obtained by delaying the input interlaced signal by one field;

field correlation detection means for detecting correlation between the input interlaced signal and the 1-field delay input interlaced signal based on the pixel level difference, and  
15 outputting N-1 inter-field correlation determination signals;

inter-field difference storage means for storing the N-1 inter-field correlation determination signals;

field/frame correlation determination means for determining, based on a pattern of values of the N-1 inter-field  
20 difference determination signals, whether two sequential fields among the N sequential fields are generated from a same frame or different frames; and

interpolation method determination means for determining, as an interpolation method, inter-field interpolation if the fields  
25 are determined to have been generated from the same frame, or

intra-field interpolation if the fields are determined to have been generated from the different frames.

In the above first aspect, sequential fields, which exceed N-1 fields corresponding to two parent frames, are targeted for determination, and correlations between at least N fields are detected. A parent-frame-to-field relationship is determined in a multistage manner based on the correlations between the N fields, achieving a significant effect of more accurately determining a method for interpolating the input interlaced signal.

Also, the parent-frame-to-field relationship is determined based on a pattern of correlations between all fields targeted for determination, whereby it is possible to achieve a significant effect of increasing accuracy in determining the method for interpolating the input interlaced signal with an increase in number of fields targeted for determination.

Also, in the case where the parent-frame-to-field relationship cannot be reliably determined, a distinction result for an input interlaced signal before determination is not changed. This prevents erroneous distinction between input interlaced signals due to an unreliable determination result, achieving a significant effect of more accurately determining the method for interpolating the input interlaced signal.

In a second aspect based on the first aspect, the device further comprises interpolation method determination delay means for delaying a determination of the interpolation method by the

interpolation method determination means by a predetermined time period.

In a third aspect based on the second aspect, the predetermined time period is determined based on a time lag from  
5 when the interpolation method of inputted fields are determined until an interpolation process is actually performed.

In a fourth aspect based on the third aspect, the predetermined time period is determined to be around 0.5 seconds based on mechanical/electrical characteristics of the field  
10 interpolation method determination device and a device which carries out the field interpolation process.

In a fifth aspect based on the second aspect, counter means increments by one count if the fields are determined to have been generated from the same frame, resets a count value if they are  
15 determined to have been generated from the different frames, or maintains the count value if otherwise, and

the interpolation method determination means selects the inter-field interpolation if the count value is greater than a predetermined value, or selects the intra-field interpolation if  
20 the count value is less than or equal to the predetermined value.

In a sixth aspect based on the first aspect, if the input interlaced signal is a 2-3 pulldown signal, N is equal to or more than 6.

In a seventh aspect based on the first aspect, if the input  
25 interlaced signal is a 2-2 pulldown signal, N is equal to or more

than 5.

In an eighth aspect based on the first aspect, if at least two sequential signals among the N-1 inter-field correlation determination signals indicate absence of correlation, the  
5 field/frame correlation determination means determines that the two sequential fields have been generated from the different frames.

In a ninth aspect based on the first aspect, if the N-1 inter-field correlation determination signals alternately  
10 indicate presence and absence of correlation, the field/frame correlation determination means determines that the two sequential fields have been generated from the same frame.

In a tenth aspect based on the first, the field correlation detection means includes:

15 pixel difference determination means for determining for each pixel whether the pixel signal level difference is greater than a first threshold which indicates a predetermined pixel level and outputting a pixel unit level difference determination result represented by a binary value;

20 field unit level difference determination means for adding one field to the pixel unit level difference determination result, and outputting a field unit level difference determination result; and

inter-field correlation determination means for  
25 determining whether inter-field correlation is significant based



on whether the field unit level difference determination result is greater than a second threshold indicating a predetermined number of pixels.

In an eleventh aspect based on the tenth aspect, the  
5 inter-field difference determination means further includes:  
signal level detection means for detecting a signal level  
indicating brightness of an image represented by the 1-field delay  
input interlaced signal; and

first threshold change means for changing the first  
10 threshold based on the value of the signal level.

In a twelfth aspect based on the tenth aspect, the inter-field  
difference determination means further includes: signal level  
detection means for detecting a signal level indicating brightness  
of an image represented by the 1-field delay input interlaced  
15 signal; and

second threshold change means for changing the second  
threshold based on the value of the signal level.

In the eleventh or twelfth aspect, a threshold for detecting  
the inter-field correlation is changed in accordance with the  
20 brightness of the image represented by the input interlaced signal,  
achieving a significant effect of more accurately detecting an  
inter-field correlation in an input interlaced signal for a dark  
visual image where the inter-field correlation is hard to detect.

In a thirteenth aspect based on the first aspect, the  
25 inter-field difference determination means further includes:

field identification means for outputting, based on the 1-field delay input interlaced signal, a field identification signal which indicates whether a field of the 1-field delay input interlaced signal is an even field or an odd field; and

5                   an AND circuit for calculating a logical product of the field identification means and the inter-field correlation determination signal, and outputting the product ( to the N inter-field difference storage means.

                  In the thirteenth aspect, a parent frame-to-field  
10 relationship is determined based on a logical product of an inter-field correlation detection result and an even field/off field detection result for an interpolation target field. Thus, it is possible to achieve a significant effect of preventing misinterpolation of a field before or after an interpolation target  
15 field which occurs due to a reversal of the order of even and odd fields, even in the case where an interlaced signal, where the order of the even and odd fields are reversed with respect to a parent frame, is inputted to a device which interpolates the field before or after the interpolation target field based on a detection  
20 result of the even field or the odd field.

                  In a fourteenth aspect based on the thirteenth aspect, the inter-field difference determination means further includes: an inverter for outputting a reversed signal of the field identification signal; and

25                   a field identification signal reverse switch for

selectively outputting either the field identification signal or the reversed signal to the AND circuit.

In the fourteenth aspect, the switch is provided for selecting an even field/odd field detection result for the interpolation target field and a reversed signal for the even field/odd field detection result, and a parent frame-to-field relationship is determined based on a logical product of the even field/odd field detection result selected by the switch and an inter-field correlation detection result. Thus, it is possible to achieve a significant effect of selecting a field separated from the same parent frame of the interpolation target field and generating the original parent frame, even in the case where an interlaced signal, where the order of the even and odd fields are reversed with respect to a parent frame, is inputted to a device which interpolates the field before or after the interpolation target field based on a detection result of the even field or the odd field.

#### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing a structure of a video signal processing device having incorporated therein a field interpolation method determination device according to a first embodiment of the present invention.

FIG. 2 is a diagram showing a detailed structure of a field interpolation method determination section shown in FIG. 1.

FIG. 3 is a table showing relationships between output values of first through fourth registers shown in FIG. 2 and signals inputted into a counter.

FIG. 4 is a diagram showing relationships between fields of input interlaced signals and frames of a progressive signal after conversion in accordance with the first embodiment of the present invention.

FIG. 5 is a block diagram showing a structure of a video signal processing device having incorporated therein a field interpolation method determination device according to a second embodiment of the present invention.

FIG. 6 is a diagram showing a detailed structure of a field interpolation method determination section shown in FIG. 5.

FIG. 7 is a block diagram showing a structure of a video signal processing device having incorporated therein a field interpolation method determination device according to a third embodiment of the present invention.

FIG. 8 is a diagram showing a detailed structure of a field interpolation method determination section shown in FIG. 7.

FIG. 9 is a block diagram showing a structure of a video signal processing device having incorporated therein a field interpolation method determination device according to a fourth embodiment of the present invention.

FIG. 10 is a block diagram showing a structure of a video signal processing device having incorporated therein a

conventional field interpolation method determination device according to a fourth embodiment of the present invention.

FIG. 11 is a diagram showing a detailed structure of a field interpolation method determination section shown in FIG. 10.

5

#### BEST MODE FOR CARRYING OUT THE INVENTION

Before specifically describing field interpolation method determination devices according to embodiments of the present invention, the basic concept of the present invention is now described. As described in relation to conventional techniques, an erroneous determination by a field interpolation method determination device is caused because there is no difference, or only a slight difference, between parent frames, so that a difference between fields converted from two different frames.

15 In the case where fields targeted for determination include only one border between parent frames, so that it is not possible to detect a difference between two parent frames of an input interlaced signal, the conventional field interpolation method determination device determines to carry out intra-interpolation.

20 However, even in the case where no difference between two parent frames can be specifically detected, if the number of fields targeted for determination is increased so as to increase inter-parent frame borders among the fields, it is made possible to evaluate correlations between parent frames and fields in a  
25 multistage manner.

From this point of view, it is apparent that the field interpolation method determination device can more accurately identify a video signal if the number of fields targeted for determination is increased. That is, in order to more accurately  
5 identify the video signal, it is desirable to increase the number of fields targeted for determination to infinity. However, it also increases the number of registers for storing differences between fields, resulting in an infinite increase in cost of the field interpolation method determination device.

10 Accordingly, in the present invention, the number of fields targeted for determination is dynamically changed based on differences between a predetermined number or more of fields including at least two inter-field borders. Accordingly, if the number of fields converted from two parent frames is  $N-1$ ,  
15 differences between at least  $N$  fields are targeted for determination. That is, the number of differences between fields targeted for determination is at least  $N-1$ .

Also, if a difference between parent frames is insignificant, and therefore cannot be detected as a difference between fields,  
20 a threshold for determining an inter-field difference is dynamically changed in order to detect a smaller inter-field difference.

In the present invention, the number of fields targeted for determination or the threshold for detecting the inter-field  
25 difference is dynamically changed based on the above technical

idea, making it possible to more accurately identify a video signal.

Also, as described above, in a telecine-converted signal in which positional relationships between fields converted from parent frames are reversed, two fields converted from different parent frames are interpolated with each other to form a frame. As a result, different images are contained in one frame, and therefore video quality of a progressive signal obtained by conversion is considerably deteriorated.

Such an interlaced signal, where positional relationships between fields converted from parent frames are reversed, is opposite to an ordinary telecine-converted signal in terms of relationships in size between fields and relationships between odd and even fields. Therefore, in the present invention, a signal, which indicates correlation between fields, is corrected by a detection signal, which indicates whether fields are odd-/even-numbered, thereby preventing fields converted from different frames from being subjected to mutual inter-field interpolation.

In the present invention, relationships between fields and parent frames in an interlaced signal converted from a progressive signal are determined, and each field of the interlaced signal is interpolated using inter-field interpolation or intra-field interpolation. Described below is a case where a 2-2 pulldown telecine-converted signal is detected as a typical example of a signal obtained by converting the progressive signal into the

interlaced signal.

(First Embodiment)

Referring to FIG. 1, a video signal processing device having incorporated therein a field interpolation method determination  
5 device according to the present invention is described. A video signal processing device 100a shown in the figure is operable to determine relationships between fields and parent frames in an input interlaced signal, and if the input interlaced signal is a telecine-converted signal, it converts the fields of the input  
10 interlaced signal into frames of a progressive signal by performing inter-field interpolation. On the other hand, if the input interlaced signal is not a telecine-converted signal, the video signal processing device 100a converts the fields of the input interlaced signal into the frames of the progressive signal by  
15 performing intra-field interpolation.

The video signal processing device 100a includes an input terminal 1, a field memory 2, a field memory 4, a subtractor 6, a field interpolation method determination section 8a, an ODD/EVEN detection section 10, a first switch 12, a line memory 14, a 2-line  
20 interpolation section 16, a second switch 18, and a progressive signal generation section 20.

The input terminal 1, the field memory 2, the field memory 4, the subtractor 6, the ODD/EVEN detection section 10, the first switch 12, the line memory 14, the 2-line interpolation section  
25 16, the second switch 18, and the progressive signal generation



section 20 are the same as those of the conventional video signal processing device 200 shown in FIG. 11, and therefore the descriptions thereof are omitted.

The field interpolation method determination section 8a  
5 determines determines relationships between fields and parent frames in the input interlaced signal based on an inter-field pixel level difference  $S_p$ , and determines whether to use either inter-field interpolation or intra-field interpolation to convert a 1-field delay input interlaced signal  $V_{d1}$  into a progressive  
10 signal.

Referring to FIG. 2, a configuration of the field interpolation method determination section 8a is described. The field interpolation method determination section 8a includes an absolute value circuit 81, a pixel difference determination  
15 comparator 82, a cumulative adder 83, an inter-field correlation determination comparator 84, a first register 85, a second register 86, a third register 87, a fourth register 88, a 4-field correlation determination comparator 89, a reset determination circuit 90, and a switch 91.

20 Although not shown, a field pulse VP and a frame pulse FP are generated by a timing generation circuit.

The absolute value circuit 81 obtains an absolute value of the inter-field pixel level difference  $S_p$  calculated by the subtractor 6, and outputs it as an inter-field pixel level  
25 difference absolute value  $S_{pA}$ . Note that, in the interlaced signal,

scanning lines of adjacent fields are displaced by one row from each other. Accordingly, the subtractor 6 obtains a difference between an average pixel level for two adjacent lines in one field and a corresponding pixel level in the other field.

5           The pixel difference determination comparator 82 compares the inter-field pixel level difference absolute value  $SpA$  with a predetermined first threshold  $X$  to provide a determination as to whether two fields have at least a great difference (a significant difference) in pixel level to such an extent that they are considered  
10 as being derived from the same parent frame.

          Accordingly, the first threshold  $X$  is set so as to correspond to a difference in pixel level which can be determined not to significantly differ from a difference in pixel level between fields separated from the same frame. Then, as an inter-field  
15 pixel difference determination signal  $Dp$ , which indicates a result of the determination, the pixel difference determination comparator 82 outputs "1" if the determination is "significant difference", or outputs "0" if it is "no significant difference".

          The cumulative adder 83 outputs an inter-field pixel  
20 difference determination cumulative value  $CDp$  which is obtained by cumulatively summing inter-field pixel difference determination signals  $Dp$ . The inter-field pixel difference determination cumulative value  $CDp$  is a value which indicates the number of pixels having been determined as having a "significant  
25 difference" between fields of the input interlaced signal  $Vin$  and

the 1-field delay input interlaced signal Vd1. Note that the cumulative adder 83 is reset for each field by the field pulse VP.

The inter-field correlation determination comparator 84  
5 determines whether a field of the input interlaced signal Vin and  
a field of the 1-field delay input interlaced signal Vd1 are  
correlated to such an extent that they can be considered as being  
derived from the same frame. Specifically, the inter-field  
correlation determination comparator 84 determines that there is  
10 no correlation between the fields if the inter-field pixel  
difference determination cumulative value CDp is greater than a  
predetermined threshold Y. On the other hand, the inter-field  
correlation determination comparator 84 determines that there is  
correlation between fields if the inter-field pixel difference  
15 determination cumulative value CDp is less than or equal to the  
predetermined threshold Y. Then, the inter-field correlation  
determination signal Df indicating a result of the determination  
is outputted.

The value of the inter-field correlation determination  
20 signal Df is "0" if there is correlation, or "1" if there is no  
correlation.

The first register 85, the second register 86, the second  
register 87, and the fourth register 88 are D-flip-flops, and  
supplied with the field pulse VP as a clock. These four registers  
25 sequentially store a corresponding one of four sequential

inter-field correlation determination signals Df. Also, values of the stored four inter-field correlation determination signals are outputted as register output signals (R1-R4).

The 4-field correlation determination comparator 89  
5 compares the four register output signals (R1-R4) with a telecine determination table Tc to determine whether the current input video signal has an inter-field correlation pattern of a telecine-converted signal.

A table TC shown in FIG. 3 is the telecine determination  
10 table Tc. If output values of the four register output signals (R1-R4) shown in the table Tc are respectively "0101" or "1010", inter-field correlation matches the characteristic of a 2-2 pulldown telecine-converted signal in which large and small values alternate with each other. In this case, the 4-field correlation  
15 determination comparator 89 determines that the input interlaced signal Vin is a telecine-converted signal. Then, the 4-field correlation determination comparator 89 outputs a telecine determination signal Ds.

The reset determination circuit 90 compares the four register  
20 output signals (R1-R4) with a reset determination table Tr to reliably determine whether the current input video signal is a telecine-converted signal.

A table Tr shown in FIG. 3 is the reset determination table Tr. Even if any value of the four register output signals (R1-R4)  
25 which is equal to "0" is changed to "1", all patterns shown in

the reset table Tr cannot correspond to either "0101" or "1010" which matches the inter-field correlation pattern of the 2-2 pulldown telecine-converted signal.

That is, it can be reliably determined that the input  
5 interlaced signal Vin is not the 2-2 pulldown telecine-converted signal. Accordingly, the reset determination circuit 90 outputs a reset signal Rst.

Also, a table T1 shown in FIG. 3 shows four register output signals (R1-R4) which do not belong to either the telecine  
10 determination table Tc or the reset determination table Tr. Each set of output values of the registers shown in the table T1 matches the inter-field correlation pattern of the 2-2 pulldown telecine-converted signal if the output value of at least one register is changed from "0" to "1".

15 The switch 91 outputs, based on the telecine determination signal Ds and the reset signal, a field interpolation method instruction signal Dv1 that instructs to perform either inter-field interpolation or intra-field interpolation on the 1-field delay input interlaced signal Vd1.

20 Specifically, the switch 91 outputs a field interpolation method instruction signal Dv1 that instructs to perform inter-field interpolation if the telecine determination signal Ds is outputted, while it outputs a field interpolation method instruction signal Dv1 that instructs to perform intra-field interpolation if the  
25 reset signal Rst is outputted. Also, if neither the telecine

determination signal Ds nor the reset signal Rst is outputted, the switch 91 does not change the field interpolation method instruction signal Dv1.

Next, referring to FIG. 4, an operation of the video signal processing device 100a is described. The input interlaced signal Vin is obtained by converting parent frames A, B, and C of a progressive signal into A1 and A2, B1 and B2, and C1 and C2, respectively. Fields of the input interlaced signal Vin1 are entered in "field No." in the order from smallest to largest.

Correlation between two fields is determined based on a difference between the input interlaced signal Vin and the 1-field delay input interlaced signal Vd1. For example, correlation between field B2 in field No. 4 of the input interlaced signal Vin and field B1 of the 1-field delay input interlaced signal Vd1 is determined. In this case, the fields are both converted from the same frame B, and therefore a difference therebetween is small. That is, they are determined as having a correlation, and the value of the field correlation determination signal Df is "0".

As for field No. 5 of the input interlaced signal Vin, field C1 of the input interlaced signal Vin and field B2 of the 1-field delay input interlaced signal Vd1 are converted from different frames, and therefore there is a large difference therebetween. That is, they are determined as having no correlation, and the value of the field correlation determination signal Df is "1".

The field correlation determination signal Df sequentially

stored into four registers 85-88, and four sequential register outputs are represented by "0101" or "1010".

As such, if values of the field correlation determination signal Df are "0101" or "1010", the switch 91 outputs a signal  
5 that instructs to perform inter-field interpolation as the interpolation method instruction signal Dv1.

In this case, the first switch 12 selects either the input interlaced signal Vin or the 2-field delay input interlaced signal Vd2 based on a field identification signal Doe obtained by the  
10 ODD/EVEN detector 10.

Specifically, if the 1-field delay input interlaced signal Vd1 corresponds to an odd field, the input interlaced signal Vin is selected. On the other hand, if the 1-field delay input interlaced signal Vd1 corresponds to an even field, the 2-field  
15 delay input interlaced signal Vd2 is selected.

For example, if the field B2 in field No. 4 is inputted as the input interlaced signal Vin, a field inputted as an interpolation target signal to the progressive signal generation section 20 is the field B1 in field No. 3. In this case, inter-field  
20 interpolation is performed using the field B2, which is the input interlaced signal Vin, as an interpolation signal Sw2 to generate the original parent frame B.

Also, if field C1 in field No. 5 is inputted as the input interlaced signal Vin, a field inputted as an interpolation target  
25 signal to the progressive signal generation section 20 is the field

B2 in field No. 4. In this case, inter-field interpolation is performed using the field B1, which is the 2-field delay input interlaced signal Vd2, as the interpolation signal Sw2 to generate the original parent frame B.

5           In the conventional field interpolation method determination device, correlation between two fields containing only one border between parent frames is used as a determination target to detect a correspondence between parent frames and fields, thereby detecting a telecine-converted signal. Then, in the case  
10 where no difference between frames can be detected, the correspondence between parent frames and fields is unclear, and therefore the field interpolation method determination device determines that the input interlaced signal is not a telecine-converted signal.

15           On the other hand, in the field interpolation method determination device according to the present embodiment, differences between fields in such a number as to contain two or more inter-frame borders are targeted for determination. Accordingly, even if a difference between frames cannot be detected,  
20 it is possible to determine whether the input interlaced signal is the telecine-converted signal based on a plurality of inter-frame differences. Also, a plurality of frame borders are contained in the determination target, and therefore it is possible to evaluate all fields targeted for determination in a multistage  
25 manner based on a determination about each frame border.



Accordingly, even if no inter-frame difference can be detected, an intermediate determination is not made to immediately provide a determination of not being the telecine-converted signal. Therefore, even if an inter-frame difference cannot be specifically  
5 detected, a previous field interpolation method is not changed, causing no reduction in image quality due to an erroneous instruction to perform intra-field interpolation. Thus, even if the telecine-converted signal from which any inter-frame difference is difficult to detect is inputted, the field  
10 interpolation method determination device according to the present embodiment is able to more accurately determine a field interpolation method.

(Second Embodiment)

Referring to FIG. 5, a video signal processing device having  
15 incorporated therein a field interpolation method determination device according to a second embodiment of the present invention is described. The field interpolation method determination device according to the present embodiment is characterized in that even in the case where a visual image is dark, so that a  
20 difference in pixel level between parent frames is small, a threshold for determining an inter-field pixel difference can be changed in accordance with the brightness of the visual image, whereby it is possible to detect an inter-field difference resulted from an inter-frame difference.

25 Accordingly, a configuration of a video signal processing

device 100b shown in FIG. 5 is different from that of the video signal processing device according to the first embodiment in that the field interpolation method determination section 8a is replaced with a field interpolation method determination section 8b. In order to avoid redundant descriptions, the same elements as those of the video signal processing device according to the first embodiment are not described.

The video signal processing device 100b includes an input terminal 1, a field memory 2, a field memory 4, a subtractor 6, a field interpolation method determination section 8b, an ODD/EVEN detection section 10, a first switch 12, a line memory 14, a 2-line interpolation section 16, a second switch 18, and a progressive signal generation section 20.

The field interpolation method determination section 8b determines determines relationships between fields and parent frames in an input interlaced, based on a 1-field delay input interlaced signal Vd1 and an inter-field pixel level difference Sp, and determines whether to use either inter-field interpolation or intra-field interpolation to convert the 1-field delay input interlaced signal Vd1 into a progressive signal.

Referring to FIG. 6, a configuration of the field interpolation method determination section 8b is described. The configuration of the field interpolation method determination section 8b is different from that of the field interpolation method determination section 8a according to the first embodiment in that

the switch 91 is replaced by a counter 92 and a count determination comparator 93, and an auto picture level (APL) detector 94b and a pixel difference threshold change section 95b are added.

The field interpolation method determination section 8b includes an absolute value circuit 81, a pixel difference determination comparator 82, a cumulative adder 83, an inter-field correlation determination comparator 84, a first register 85, a second register 86, a third register 87, a fourth register 88, a 4-field correlation determination comparator 89, a reset determination circuit 90, the counter 92, the count determination comparator 93, the auto picture level detector 94b, and the pixel difference threshold change section 95b.

The auto picture level detector 94b detects a signal level PL of the 1-field delay input interlaced signal Vd1. The signal level PL is increased as a visual image becomes brighter, while it is decreased as the image becomes darker.

The pixel difference threshold change section 95b changes the value of a pixel difference threshold Xb based on the signal level PL in accordance with a predetermined rule. For example, values of a plurality of pixel difference thresholds Xb may be predetermined so as to correspond to degrees of the signal level PL, making it possible to output the value of a corresponding pixel difference threshold Xb in accordance with an inputted signal level PL, or the value of the pixel difference threshold Xb may be obtained based on the signal level PL in accordance with a predetermined

mathematical expression.

In any case, settings are made such that the pixel difference threshold  $X_b$  is increased as the signal level  $PL$  becomes higher, and decreased as the signal level  $PL$  becomes lower.

5           Therefore, in the case where the 1-field delay input interlaced signal  $V_{d1}$  corresponds to a dark visual image, the value of the pixel difference threshold  $X_b$  is small, and therefore the pixel difference determination comparator 82 determines that there is a difference in pixel level between fields even if the difference  
10 in pixel level is smaller. On the other hand, in the case where the 1-field delay input interlaced signal  $V_{d1}$  corresponds to a bright visual image, the value of the pixel difference threshold  $X_b$  is large, and therefore it is possible to prevent an erroneous determination that there is a difference in pixel level between  
15 fields converted from the same frame.

The counter 92 counts a telecine determination cumulative value  $CDs$  which is incremented by the telecine determination signal  $Ds$ . Also, it is reset by the reset signal  $Rst$ .

Also, as described above, if there is no difference or only  
20 a slight difference between parent frames, no difference between fields converted from different frames is detected, and therefore in some cases, it is not determined as being a telecine-converted signal even if it is the telecine-converted signal. Accordingly, in the case where it is not possible to reliably determine whether  
25 the input interlaced signal  $V_{in}$  is the telecine-converted signal,

the count of the telecine determination counter 92 is not changed.

If the telecine determination cumulative value CDs of the counter 92 exceeds a predetermined threshold Z, the count determination comparator 93 outputs a field interpolation method instruction signal Dv1 that instructs to perform inter-field interpolation on fields of the 1-field delay input interlaced signal Vd1, in order to enhance the stability of the field interpolation method determination section 8b. The threshold Z is set so as to correspond to a time period from when the telecine determination signal Ds is outputted until inter-field interpolation is actually implemented, and normally it is set so as to be 0.5 seconds.

That is, the video signal processing device according to the present embodiment has no potential for erroneous detection even in the case of a bright visual image, and is able to more accurately detect an inter-field difference even if a difference in pixel level between frames is small because of a dark visual image.

Note that in the present embodiment, although it is assumed that the first threshold X is dynamically changed based on the signal level PL of the 1-field delay input interlaced signal Vd1, the second threshold Y may be changed. This allows a determination that there is an inter-field difference even if there is only a small number of pixel levels which represent a significant difference between fields, achieving an effect similar to that

achieved in the case of changing the first threshold X.

(Third Embodiment)

Referring to FIG. 7, a video signal processing device having incorporated therein a field interpolation method determination  
5 device according to a third embodiment of the present invention is described. In the field interpolation method determination devices according to the first and second embodiments, if an interlaced signal in which positional relationships between odd and even fields with respect to parent frames are reversed is  
10 inputted, inter-field interpolation is performed on fields of different parent frames. As described above, if inter-field interpolation is performed on fields converted from different parent frames, video quality of a frame to be generated is considerably deteriorated.

15 The field interpolation method determination device according to the present embodiment is characterized by preventing inter-field interpolation from being erroneously performed on fields converted from different frames, even in the case of receiving an interlaced signal, where positional relationships  
20 between odd and even fields with respect to parent frames are reversed, in other words, an interlaced signal, where each parent frame is converted into an even field and an odd field following immediately thereafter.

Accordingly, a configuration of the video signal processing  
25 device 100c shown in FIG. 7 is different from that of the video

signal processing device according to the first embodiment in that the field interpolation method determination section 8a is replaced with a field interpolation method determination section 8c. In order to avoid redundant descriptions, the same elements as those of the video signal processing device according to the first  
5 embodiment are not described.

The video signal processing device 100c includes an input terminal 1, a field memory 2, a field memory 4, a subtractor 6, a field interpolation method determination section 8c, an  
10 ODD/EVEN detection section 10, a first switch 12, a line memory 14, a 2-line interpolation section 16, a second switch 18, and a progressive signal generation section 20.

The field interpolation method determination section 8c determines determines relationships between fields and parent  
15 frames in an input interlaced based on a field identification signal Doe and an inter-field pixel level difference Sp, and determines whether to using either inter-field interpolation or intra-field interpolation to convert a 1-field delay input interlaced signal Vd1 into a progressive signal.

Referring to FIG. 8, a configuration of the field  
20 interpolation method determination section 8c is described. The configuration of the field interpolation method determination section 8c is different from the field interpolation method determination section 8 according to the first embodiment that  
25 an AND circuit 96c is added.

The field interpolation method determination section 8c includes an absolute value circuit 81, a pixel difference determination comparator 82, a cumulative adder 83, an inter-field correlation determination comparator 84, a first register 85, a second register 86, a third register 87, a fourth register 88, a 4-field correlation determination comparator 89, a reset determination circuit 90, a counter 92, a count determination comparator 93, and the AND circuit 96c.

The AND circuit 96c obtains a logical product of an inter-field difference signal Df and a field identification signal Doe, and outputs a modified inter-field difference signal Dfa. Referring to FIG. 4, the modified inter-field difference signal Dfa is described.

In the case where an ordinary telecine-converted signal is inputted, the value of the inter-field difference signal Df is "0" if the 1-field delay input interlaced signal Vd1 corresponds to an odd field, and the value of the inter-field difference signal Df is "1" if the 1-field delay input interlaced signal Vd1 corresponds to an even field.

The ODD/EVEN detection section outputs "0" as the field identification signal Doe if the 1-field delay input interlaced signal Vd1 corresponds to an odd field, while it outputs "0" as the field identification signal Doe if the 1-field delay input interlaced signal Vd1 corresponds to an even field.

In this case, the value of the modified inter-field



difference signal Dfa is equal to that of the inter-field difference signal Df, and therefore a telecine detection signal Vd3, which indicates a detection result of the telecine-converted signal, is not affected.

5           Next, consider a case where an interlaced signal, in which positional relationships between odd and even fields with respect to parent frames are reversed, is inputted. In this case, contrary to the foregoing, if the 1-field delay input interlaced signal Vd1 corresponds to an odd field, the value of the inter-field  
10 difference signal Df is "1", and if the 1-field delay input interlaced signal Vd1 corresponds to an even field, the value of the inter-field difference signal Df is "0".

          Since the value of the field identification signal Doe does not change, the value of any modified inter-field difference signal  
15 Dfa is "0". Accordingly, the counter 92 is not incremented, so that no telecine detection signal Dv3 is outputted. As a result, intra-field interpolation is performed instead of inter-field interpolation.

          Thus, even in the case where the interlaced signal, in which  
20 positional relationships between odd and even fields with respect to parent frames are reversed, is inputted, it is possible to prevent inter-field interpolation from being performed on fields converted from different frames.

          In the field interpolation method determination device  
25 according to the present embodiment, a considerable reduction in

video quality is prevented, but because inter-field interpolation is carried out, even in the case of the telecine-converted signal, it is not possible to carry out a reconversion to the original parent frame to enhance vertical resolution.

5           (Fourth Embodiment)

A field interpolation method determination device according to a fourth embodiment is characterized by performing inter-field interpolation on fields converted from the same parent frame even in the case where an interlaced signal, in which positional  
10 relationships between odd and even fields with respect to parent frames are reversed, is inputted.

Referring to FIG. 9, a video signal processing device having incorporated therein a field interpolation method determination device according to the present embodiment is described.

15           The field interpolation method determination device according to the present embodiment is characterized by selectively reversing the value of the field identification signal Doe, and outputting it to the field interpolation method determination section 8c and the first switch 12.

20           Accordingly, a configuration of the video signal processing device 100c shown in FIG. 9 is different from that of the video signal processing device according to the third embodiment in that an inverter 22d and a field identification signal reverse switch are added. In order to avoid redundancy of descriptions, the same  
25 elements as those of the video signal processing device according

to the first embodiment are not described.

The video signal processing device 100d includes an input terminal 1, a field memory 2, a field memory 4, a subtractor 6, a field interpolation method determination section 8c, an  
5 ODD/EVEN detection section 10, a first switch 12, a line memory 14, a 2-line interpolation section 16, a second switch 18, a progressive signal generation section 20, the inverter 22d, and the field identification signal change switch 23d.

The inverter 22d receives a field identification signal Doe,  
10 inverts the value of the signal, and outputs a field identification inverted signal nDoe.

The field identification signal change switch 23d selectively outputs, as a field identification signal Swf, either the field identification signal Doe or the field identification  
15 inverted signal nDoe.

In the case where an interlaced signal, in which positional relationships between odd and even fields with respect to parent frames are reversed, is inputted, the field identification signal change switch 23d is operated such that a signal, which is outputted  
20 to the field interpolation method determination section 8c and the first switch 12, is switched to the field identification inverted signal nDoe.

In this case, in the field interpolation method determination section 8c and the first switch 12, even the interlaced signal,  
25 in which positional relationships between odd and even fields with

respect to parent frames are reversed, is handled in a manner similar to an ordinary interlaced signal.

Accordingly, the field interpolation method determination section 8c is able to detect a telecine-converted signal, while  
5 the first switch 12 is able to suitably select an inter-field interpolation signal. Thus, the video signal processing device according to the present embodiment is able to convert even the interlaced signal, in which positional relationships between odd and even fields with respect to parent frames are reversed, into  
10 a progressive signal with vertical resolution enhanced by inter-field interpolation.

#### INDUSTRIAL APPLICABILITY

As described above, the present invention provides a field  
15 interpolation method determination device capable of dynamically changing the number of fields targeted for determination and a threshold for determining correlation between fields even in the case where it is not possible or it is difficult to specifically detect a difference between parent frames, and capable of  
20 accurately detecting relationships between fields and parent frames in an input interlaced signal, thereby determining whether to perform either inter-field interpolation or intra-field interpolation.